

5G NR modules

Product		RM520N	RM530N-GL
			
Form factor		M.2	M.2
Dimensions (mm)		52.0 × 30.0 × 2.3	52.0 × 30.0 × 2.3
5G		Sub-6 GHz	Sub-6 GHz/mmWave
Frequency bands (MHz)	-GL (Global)	5G NR: n1/2/3/5/7/8/12/13/14/18/20/25/26/28/29/30/38/40/41/48/66/70/71/75/76/77/78/79; LTE-FDD: B1/2/3/4/5/7/8/12/13/14/17/18/19/20/25/26/28/29/30/32/66/71; LTE-TDD: B34/38/39/40/41/42/43/48; LAA: B46; WCDMA: B1/2/4/5/8/19	5G NR: n1/2/3/5/7/8/12/13/14/18/20/25/26/28/29/30/38/40/41/48/66/70/71/75/76/77/78/79/257/258/260/261; LTE-FDD: B1/2/3/4/5/7/8/12/13/14/17/18/19/20/25/26/28/29/30/32/66/71; LTE-TDD: B34/38/39/40/41/42/43/48; LAA: B46; WCDMA: B1/2/4/5/8/19
	-EU (EMEA/ APAC ¹ / Brazil)	5G NR: n1/3/5/7/8/20/28/38/40/41/71/75/76/77/78; LTE-FDD: B1/3/5/7/8/20/28/32/71; LTE-TDD: B38/40/41/42/43; WCDMA: B1/5/8	/
Weight (approx.) (g)		8.7	8.8
Operating temperature		-30°C ~ +75°C	-30°C ~ +75°C
Extended temperature		-40°C ~ +85°C	-40°C ~ +85°C
Control via AT commands		3GPP TS27.007 and Quectel Enhanced AT Commands	3GPP TS27.007 and Quectel Enhanced AT Commands
Data transmission (Max.) ²			
5G SA Sub-6		2.4 Gbps (DL)/900 Mbps (UL)	2.4 Gbps (DL)/900 Mbps (UL)
5G NSA Sub-6		3.4 Gbps (DL)/550 Mbps (UL)	3.4 Gbps (DL)/550 Mbps (UL)
5G NSA mmWave		/	4.0 Gbps (DL)/1.4 Gbps (UL)
LTE		LTE-FDD: 1.6 Gbps (DL)/200 Mbps (UL)	LTE-FDD: 1.6 Gbps (DL)/200 Mbps (UL)
UMTS (Mbps)		WCDMA: 42 (DL)/5.76 (UL)	WCDMA: 42 (DL)/5.76 (UL)
SMS		•	•
Protocols		TCP/UDP/FTP/HTTP/HTTPS/PING/SMS	TCP/UDP/FTP/HTTP/HTTPS/PING/SMS
Interfaces			
(U)SIM		× 2	× 2
USB		2.0/3.0/3.1	2.0/3.0/3.1
PCIe		PCIe 3.0	PCIe 3.0
Antenna		Sub-6/GNSS × 4 (RM520N-CN/RM520N-GL); Sub-6/GNSS: 4+1 (optional) (RM520N-EU)	Sub-6/GNSS × 4, mmWave × 2
Enhanced features			
MIMO		Sub-6: DL 4 × 4, UL 2 × 2	Sub-6: DL 4 × 4, UL 2 × 2 mmWave: DL 2 × 2, UL 2 × 2
Voice		Optional ³	Optional
DTMF		Dual-tone Multi-frequency	Dual-tone Multi-frequency
DFOTA		Delta Firmware over the Air	Delta Firmware over the Air
GNSS		GPS/GLONASS/BDS/Galileo/QZSS	GPS/GLONASS/BDS/Galileo/QZSS
(U)SIM card detection		•	•
Electrical features			
Supply voltage range		3.135 V ~ 4.4 V, typ. 3.7 V	3.135 V ~ 4.4 V, typ. 3.7 V
Power consumption		195 µA @ Power off; 4.7 mA @ Sleep; 40mA @ USB 2.0, Idle; 60 mA @ USB 3.0, Idle	173µA@Power off; 5.1mA@Sleep; 51mA@USB2.0, Idle; 69.4mA@USB3.0, Idle
Software features			
USB serial driver		Windows 8.1/10/11, Linux 2.6~6.7, Android 4.x ~ 13	Windows 8.1/10/11, Linux 2.6~6.7, Android 4.x ~ 13
GNSS driver		Android 4.x ~ 13	Android 4.x ~ 13
RIL driver		Android 4.x ~ 13	Android 4.x ~ 13
NDIS driver		Windows 8.1/10/11	Windows 8.1/10/11
MBIM driver		Windows 8.1/10/11, Linux 3.18~6.7	Windows 8.1/10/11, Linux 3.18~6.7
Gobinet driver		Linux 2.6~6.7	Linux 2.6~6.7
QMI_WWAN driver		Linux 3.4~6.7	Linux 3.4~6.7
PCIe driver		Windows 10/11, Linux 3.10~6.7	Windows 10/11, Linux 3.10~6.7
Certifications ³		T-Mobile/Verizon/AT&T/NTT DOCOMO/Deutsche Telekom/Telefónica/Telstra/KT/GCF/PTCRB/CE/Anatel/CCC/RCM/IC/FCC/JATE/TELEC/KC/NCC/SRRC	Quectel will provide technical support for customer to certify RM530N-GL based device directly
Recommended applications		Industrial routers, industrial PDAs, rugged tablet PCs and digital signage	Industrial routers, industrial PDAs, rugged tablet PCs and digital signage

Note 1: Excl. China/Japan.

Note 2: means the data transmission is theoretical data rate and depends on network conditions.

Note 3: May depend on modules' variant.

* Planning/ Under development/ In progress

• Supported